





## 11 Description

The Isolating Amplifier D461 is an intrinsic safety associated apparatus for use in a safe area. It provides power to external speed sensors from an isolating switching transformer and conditions the associated speed signals for electronic measurements, alarms, totalizers, or controllers using an opto-coupler circuit.

The non-intrinsically safe circuitry is powered by an isolating switching transformer and monitors the speed sensor supply circuit for lead faults and annunciated by an alarm relay. The enclosure of the Isolating Amplifier D461 is designed to be installed on a DIN rail and meets the requirements of environmental protection IP 20.

### Nomenclature:

**D461      R1      \*\* U \***  
**A          B          C          D**

Where

A =            D461            Type of Device  
 B =            R1              Release 1  
 C =            11              Device one signal channel input, one signal channel output.  
                  12              Device one signal channel input, two signal channel output parallel.  
                  21              Device two signal channel input, two signal channel output  
 D =            1              Supply Voltage 18 to 40 Vac/Vdc  
                  2              Supply Voltage 85 to 250 Vac

### Ratings

#### IS Sensor Outputs:

Terminals:	S1/4	22	Signal 2
	S1/3	23	Signal 1
	S1/2	24	+Sensor Feed
	S1/1	25	GND/Sensor Feed
Uo:	8.7 V		
Io:	64 mA		
Po:	384 mW		
Lo:	IIC	7.9 mH	
	IIB	38 mH	
Co:	IIC	5.9 µF	
	IIB	50 µF	
Note: Combined Lo and Co for Signal 1 and Signal 2			



CML 15ATE2128X  
Issue 2

### Power Supply:

Terminals	S3/1	1	L
	S3/2	2	N
Um (U1):	60 V		
Um (U2):	250 V		

### Signal Outputs

Terminals:	S2/1	10	Output reference
	S2/2	11	Signal Output 1
	S2/3	12	Signal Output 2
	S2/4	13	Logic Alarm Output
Um:	60 V		

### Signal Outputs

Terminals:	S3/3	6	Relay Alarm Output
	S3/4	8	Relay Alarm Output
Um:	60 V		
Relay Contacts:	30 Vdc, 2 A		

### Variation 1

This variation introduces the following modifications:

- i. Repositioning of fuses F1 and F2 in the circuit
- ii. Removal of fuse F4
- iii. Change of thyristor package
- iv. Change of capacitor values
- v. Addition of a capacitor
- vi. Addition of 2 ferrite inductors
- vii. Addition of conformal coating to 230V version
- viii. Modification to PCB tracking

## 12 Certificate history and evaluation reports

Issue	Date	Associated report	Notes
0	18/01/2017	R606A/00	Issue of prime certificate
1	13/10/2017	R11323A/00	Introduction of Variation 1
2	21/01/2019	R12231A/00	To transfer certificate to CML B.V

Note: Drawings that describe the equipment or component are listed in the Annex.



**CML 15ATE2128X  
Issue 2**

### **13 Conditions of manufacture**

The following conditions are required of the manufacturing process for compliance with the certification.

- 13.1 Where the product incorporates certified parts or safety critical components, the manufacturer shall ensure that any changes to those parts or components do not affect the compliance of the certified product that is the subject of this certificate.
- 13.2 IEC 60079-11:2011 CL 11.2 Routine Tests for Infallible Transformers All transformers are shall subjected to following routine verification and test voltages:
- 2,500 V, between input and output windings;
  - 1,000 V between all the windings and the core;
  - 1,500 V between each winding which supplies an intrinsically safe circuit and any other output winding;

The test voltage shall be applied for a period of at least 60 s.

Alternatively, the test may be carried out at 1,2 times the test voltage, but with reduced duration of at least 1 s.

The applied voltage shall remain constant during the test. The current flowing during the test shall not increase above that which is expected from the design of the circuit and shall not exceed 5 mA r.m.s. at any time. During these tests, there shall be no breakdown of the insulation between windings or between any winding and the core or the screen.

### **14 Special Conditions for Safe Use (Conditions of Certification)**

The following conditions relate to safe installation and/or use of the equipment.

- 14.1 The values of Co and Lo apply when one of the two conditions below is given:
- The total Li of the external circuit (excluding the cable) is < 1% of the Lo value, or
  - The total Ci of the external circuit (excluding the cable) is < 1% of the Co value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
- The total Li of the external circuit (excluding the cable) > 1% of the Lo, and
  - The total Ci of the external circuit (excluding the cable) > 1% of the Co.

Note: the reduced capacitance of the external circuit (including cable) shall not be greater than 1 uF for IIB and 600 nF for IIC.